

## LF155/LF156/LF157 Series Monolithic JFET Input Operational Amplifiers

### General Description

These are the first monolithic JFET input operational amplifiers to incorporate well matched, high voltage JFETs on the same chip with standard bipolar transistors (BI-FET™ Technology). These amplifiers feature low input bias and offset currents/low offset voltage and offset voltage drift, coupled with offset adjust which does not degrade drift or common-mode rejection. The devices are also designed for high slew rate, wide bandwidth, extremely fast settling time, low voltage and current noise and a low 1/f noise corner.

### Advantages

- Replace expensive hybrid and module FET op amps
- Rugged JFETs allow blow-out free handling compared with MOSFET input devices
- Excellent for low noise applications using either high or low source impedance—very low 1/f corner
- Offset adjust does not degrade drift or common-mode rejection as in most monolithic amplifiers
- New output stage allows use of large capacitive loads (5,000 pF) without stability problems
- Internal compensation and large differential input voltage capability

### Applications

- Precision high speed integrators
- Fast D/A and A/D converters
- High impedance buffers
- Wideband, low noise, low drift amplifiers
- Logarithmic amplifiers

### Common Features


(LF155A, LF156A, LF157A)

■ Low input bias current	30 pA
■ Low Input Offset Current	3 pA
■ High input impedance	10 <sup>12</sup> Ω
■ Low input offset voltage	1 mV
■ Low input offset voltage temp. drift	3 μV/°C
■ Low input noise current	0.01 pA/√Hz
■ High common-mode rejection ratio	100 dB
■ Large dc voltage gain	106 dB

### Uncommon Features

	LF155A	LF156A	LF157A (AV=5)	Units
■ Extremely fast settling time to 0.01%	4	1.5	1.5	μs
■ Fast slew rate	5	12	50	V/μs
■ Wide gain bandwidth	2.5	5	20	MHz
■ Low input noise voltage	20	12	12	nV/√Hz

### Simplified Schematic



\*3 pF in LF157 series.

TL/H/5646-1

BI-FET™, BI-FET II™ are trademarks of National Semiconductor Corporation.

## Absolute Maximum Ratings

If Military/Aerospace specified devices are required, contact the National Semiconductor Sales Office/Distributors for availability and specifications.

(Note 8)

	LF155A/6A/7A	LF155/6/7	LF355B/6B/7B LF255/6/7	LF355/6/7 LF355A/6A/7A
Supply Voltage	$\pm 22V$	$\pm 22V$	$\pm 22V$	$\pm 18V$
Differential Input Voltage	$\pm 40V$	$\pm 40V$	$\pm 40V$	$\pm 30V$
Input Voltage Range (Note 2)	$\pm 20V$	$\pm 20V$	$\pm 20V$	$\pm 16V$
Output Short Circuit Duration	Continuous	Continuous	Continuous	Continuous
$T_{JMAX}$				
H-Package	150°C	150°C	115°C	115°C
N-Package			100°C	100°C
M-Package			100°C	100°C
Power Dissipation at $T_A = 25^\circ C$ (Notes 1 and 9)				
H-Package (Still Air)	560 mW	560 mW	400 mW	400 mW
H-Package (400 LF/Min Air Flow)	1200 mW	1200 mW	1000 mW	1000 mW
N-Package			670 mW	670 mW
M-Package			380 mW	380 mW
Thermal Resistance (Typical) $\theta_{JA}$				
H-Package (Still Air)	160°C/W	160°C/W	160°C/W	160°C/W
H-Package (400 LF/Min Air Flow)	65°C/W	65°C/W	65°C/W	65°C/W
N-Package			130°C/W	130°C/W
M-Package			195°C/W	195°C/W
(Typical) $\theta_{JC}$				
H-Package	23°C/W	23°C/W	23°C/W	23°C/W
Storage Temperature Range	$-65^\circ C$ to $+150^\circ C$			
Soldering Information (Lead Temp.)				
Metal Can Package				
Soldering (10 sec.)	300°C	300°C	300°C	300°C
Dual-In-Line Package				
Soldering (10 sec.)		260°C	260°C	260°C
Small Outline Package				
Vapor Phase (60 sec.)			215°C	215°C
Infrared (15 sec.)			220°C	220°C
See AN-450 "Surface Mounting Methods and Their Effect on Product Reliability" for other methods of soldering surface mount devices.				
ESD tolerance				
(100 pF discharged through 1.5 kΩ)	1000V	1000V	1000V	1000V

## DC Electrical Characteristics (Note 3) $T_A = T_j = 25^\circ C$

Symbol	Parameter	Conditions	LF155A/6A/7A			LF355A/6A/7A			Units
			Min	Typ	Max	Min	Typ	Max	
$V_{OS}$	Input Offset Voltage	$R_S = 50\Omega, T_A = 25^\circ C$ Over Temperature		1	2 2.5		1	2 2.3	mV mV
$\Delta V_{OS}/\Delta T$	Average TC of Input Offset Voltage	$R_S = 50\Omega$		3	5		3	5	$\mu V/^\circ C$
$\Delta TC/\Delta V_{OS}$	Change in Average TC with $V_{OS}$ Adjust	$R_S = 50\Omega, (Note 4)$		0.5			0.5		$\mu V/^\circ C$ per mV
$I_{OS}$	Input Offset Current	$T_j = 25^\circ C, (Notes 3, 5)$ $T_j \leq T_{HIGH}$		3	10 10		3	10 1	pA nA
$I_B$	Input Bias Current	$T_j = 25^\circ C, (Notes 3, 5)$ $T_j \leq T_{HIGH}$		30	50 25		30	50 5	pA nA
$R_{IN}$	Input Resistance	$T_j = 25^\circ C$		10 <sup>12</sup>			10 <sup>12</sup>		$\Omega$
$A_{VOL}$	Large Signal Voltage Gain	$V_S = \pm 15V, T_A = 25^\circ C$ $V_O = \pm 10V, R_L = 2k$ Over Temperature	50 25	200		50 25	200		V/mV V/mV
$V_O$	Output Voltage Swing	$V_S = \pm 15V, R_L = 10k$ $V_S = \pm 15V, R_L = 2k$	$\pm 12$ $\pm 10$	$\pm 13$ $\pm 12$		$\pm 12$ $\pm 10$	$\pm 13$ $\pm 12$		V V

**DC Electrical Characteristics** (Note 3)  $T_A = T_j = 25^\circ\text{C}$  (Continued)

Symbol	Parameter	Conditions	LF155A/6A/7A			LF355A/6A/7A			Units
			Min	Typ	Max	Min	Typ	Max	
$V_{CM}$	Input Common-Mode Voltage Range	$V_S = \pm 15\text{V}$	$\pm 11$	$+15.1$ $-12$		$\pm 11$	$+15.1$ $-12$		V V
CMRR	Common-Mode Rejection Ratio		85	100		85	100		dB
PSRR	Supply Voltage Rejection Ratio	(Note 6)	85	100		85	100		dB

**AC Electrical Characteristics**  $T_A = T_j = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$

Symbol	Parameter	Conditions	LF155A/355A			LF156A/356A			LF157A/357A			Units
			Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
SR	Slew Rate	LF155A/6A; $A_V = 1$ , LF157A; $A_V = 5$	3	5		10	12		40	50		V/ $\mu\text{s}$ V/ $\mu\text{s}$
GBW	Gain Bandwidth Product			2.5		4	4.5		15	20		MHz
$t_s$	Settling Time to 0.01%	(Note 7)		4			1.5			1.5		$\mu\text{s}$
$e_n$	Equivalent Input Noise Voltage	$R_S = 100\Omega$ $f = 100\text{ Hz}$ $f = 1000\text{ Hz}$		25 20			15 12			15 12		nV/ $\sqrt{\text{Hz}}$ nV/ $\sqrt{\text{Hz}}$
$i_n$	Equivalent Input Noise Current	$f = 100\text{ Hz}$ $f = 1000\text{ Hz}$		0.01 0.01			0.01 0.01			0.01 0.01		pA/ $\sqrt{\text{Hz}}$ pA/ $\sqrt{\text{Hz}}$
$C_{IN}$	Input Capacitance			3			3			3		pF

**DC Electrical Characteristics** (Note 3)

Symbol	Parameter	Conditions	LF155/6/7			LF255/6/7 LF355B/6B/7B			LF355/6/7			Units
			Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
$V_{OS}$	Input Offset Voltage	$R_S = 50\Omega$ , $T_A = 25^\circ\text{C}$ Over Temperature		3 7	5		3 6.5	5		3 10 13	10 13	mV mV
$\Delta V_{OS}/\Delta T$	Average TC of Input Offset Voltage	$R_S = 50\Omega$		5			5			5		$\mu\text{V}/^\circ\text{C}$
$\Delta T_C/\Delta V_{OS}$	Change in Average TC with $V_{OS}$ Adjust	$R_S = 50\Omega$ , (Note 4)		0.5			0.5			0.5		$\mu\text{V}/^\circ\text{C}$ per mV
$I_{OS}$	Input Offset Current	$T_j = 25^\circ\text{C}$ , (Notes 3, 5) $T_j \leq T_{HIGH}$		3 20 20	20		3 1 1	20		3 50 2	50 2	pA nA
$I_B$	Input Bias Current	$T_j = 25^\circ\text{C}$ , (Notes 3, 5) $T_j \leq T_{HIGH}$		30 50	100		30 5	100		30 200 8	200 8	pA nA
$R_{IN}$	Input Resistance	$T_j = 25^\circ\text{C}$		10 <sup>12</sup>			10 <sup>12</sup>			10 <sup>12</sup>		$\Omega$
$AVOL$	Large Signal Voltage Gain	$V_S = \pm 15\text{V}$ , $T_A = 25^\circ\text{C}$ $V_O = \pm 10\text{V}$ , $R_L = 2\text{k}$ Over Temperature	50 25	200		50 25	200		25 15	200		V/mV V/mV
$V_O$	Output Voltage Swing	$V_S = \pm 15\text{V}$ , $R_L = 10\text{k}$ $V_S = \pm 15\text{V}$ , $R_L = 2\text{k}$	$\pm 12$ $\pm 10$	$\pm 13$ $\pm 12$		$\pm 12$ $\pm 10$	$\pm 13$ $\pm 12$		$\pm 12$ $\pm 10$	$\pm 13$ $\pm 12$		V V
$V_{CM}$	Input Common-Mode Voltage Range	$V_S = \pm 15\text{V}$	$\pm 11$	$+15.1$ $-12$		$\pm 11$	$+15.1$ $-12$		$+10$	$+15.1$ $-12$		V V
CMRR	Common-Mode Rejection Ratio		85	100		85	100		80	100		dB
PSRR	Supply Voltage Rejection Ratio	(Note 6)	85	100		85	100		80	100		dB

### DC Electrical Characteristics $T_A = T_J = 25^\circ\text{C}$ , $V_S = \pm 15\text{V}$

Parameter	LF155A/155, LF255, LF355A/355B		LF355		LF156A/156, LF256/356B		LF356A/356		LF157A/157 LF257/357B		LF357A/357		Units
	Typ	Max	Typ	Max	Typ	Max	Typ	Max	Typ	Max	Typ	Max	
Supply Current	2	4	2	4	5	7	5	10	5	7	5	10	mA

### AC Electrical Characteristics $T_A = T_J = 25^\circ\text{C}$ , $V_S = \pm 15\text{V}$

Symbol	Parameter	Conditions	LF155/255/ 355/355B	LF156/256, LF356B	LF156/256/ 356/356B	LF157/257, LF357B	LF157/257/ 357/357B	Units
			Typ	Min	Typ	Min	Typ	
SR	Slew Rate	LF155/6: $A_V=1$ , LF157: $A_V=5$	5	7.5	12	30	50	$\text{V}/\mu\text{s}$ $\text{V}/\mu\text{s}$
GBW	Gain Bandwidth Product		2.5		5		20	MHz
$t_s$	Settling Time to 0.01%	(Note 7)	4		1.5		1.5	$\mu\text{s}$
$e_n$	Equivalent Input Noise Voltage	$R_S=100\Omega$ $f=100\text{ Hz}$ $f=1000\text{ Hz}$	25 20		15 12		15 12	$\text{nV}/\sqrt{\text{Hz}}$ $\text{nV}/\sqrt{\text{Hz}}$
$i_n$	Equivalent Input Current Noise	$f=100\text{ Hz}$ $f=1000\text{ Hz}$	0.01 0.01		0.01 0.01		0.01 0.01	$\text{pA}/\sqrt{\text{Hz}}$ $\text{pA}/\sqrt{\text{Hz}}$
$C_{IN}$	Input Capacitance		3		3		3	pF

### Notes for Electrical Characteristics

**Note 1:** The maximum power dissipation for these devices must be derated at elevated temperatures and is dictated by  $T_{JMAX}$ ,  $\theta_{JA}$ , and the ambient temperature,  $T_A$ . The maximum available power dissipation at any temperature is  $P_d=(T_{JMAX}-T_A)/\theta_{JA}$  or the  $25^\circ\text{C}$   $P_{dMAX}$ , whichever is less.

**Note 2:** Unless otherwise specified the absolute maximum negative input voltage is equal to the negative power supply voltage.

**Note 3:** Unless otherwise stated, these test conditions apply:

	LF155A/6A/7A LF155//6/7	LF255//6/7	LF355A/6A/7A	LF355B/6B/7B	LF355//6/7
Supply Voltage, $V_S$ $T_A$ $T_{HIGH}$	$\pm 15\text{V} \leq V_S \leq \pm 20\text{V}$ $-55^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ $+125^\circ\text{C}$	$\pm 15\text{V} \leq V_S \leq \pm 20\text{V}$ $-25^\circ\text{C} \leq T_A \leq +85^\circ\text{C}$ $+85^\circ\text{C}$	$\pm 15\text{V} \leq V_S \leq \pm 18\text{V}$ $0^\circ\text{C} \leq T_A \leq +70^\circ\text{C}$ $+70^\circ\text{C}$	$\pm 15\text{V} \leq V_S \leq \pm 20\text{V}$ $0^\circ\text{C} \leq T_A \leq +70^\circ\text{C}$ $+70^\circ\text{C}$	$V_S = \pm 15\text{V}$ $0^\circ\text{C} \leq T_A \leq +70^\circ\text{C}$ $+70^\circ\text{C}$

and  $V_{OS}$ ,  $I_B$  and  $I_{OS}$  are measured at  $V_{CM}=0$ .

**Note 4:** The Temperature Coefficient of the adjusted input offset voltage changes only a small amount ( $0.5\mu\text{V}/^\circ\text{C}$  typically) for each mV of adjustment from its original unadjusted value. Common-mode rejection and open loop voltage gain are also unaffected by offset adjustment.

**Note 5:** The input bias currents are junction leakage currents which approximately double for every  $10^\circ\text{C}$  increase in the junction temperature,  $T_J$ . Due to limited production test time, the input bias currents measured are correlated to junction temperature. In normal operation the junction temperature rises above the ambient temperature as a result of internal power dissipation,  $P_d$ .  $T_J=T_A+\theta_{JA}P_d$  where  $\theta_{JA}$  is the thermal resistance from junction to ambient. Use of a heat sink is recommended if input bias current is to be kept to a minimum.

**Note 6:** Supply Voltage Rejection is measured for both supply magnitudes increasing or decreasing simultaneously, in accordance with common practice.













**Note 7:** Settling time is defined here, for a unity gain inverter connection using  $2\text{ k}\Omega$  resistors for the LF155/6. It is the time required for the error voltage (the voltage at the inverting input pin on the amplifier) to settle to within 0.01% of its final value from the time a 10V step input is applied to the inverter. For the LF157,  $A_V=-5$ , the feedback resistor from output to input is  $2\text{ k}\Omega$  and the output step is 10V (See Settling Time Test Circuit).

**Note 8:** Refer to RETS155AX for LF155A, RETS155X for LF155, RETS156AX for LF156A, RETS156X for LF156, RETS157A for LF157A and RETS157X for LF157 military specifications.

**Note 9:** Max. Power Dissipation is defined by the package characteristics. Operating the part near the Max. Power Dissipation may cause the part to operate outside guaranteed limits.

## Typical DC Performance Characteristics













Curves are for LF155, LF156 and LF157 unless otherwise specified.















TL/H/5646-2

TL/H/5646-3


## Typical AC Performance Characteristics



## Typical AC Performance Characteristics (Continued)



## Detailed Schematic




\*C = 3 pF in LF157 series.


TL/H/5646-13

## Connection Diagrams (Top Views)

Metal Can Package (H)



Dual-In-Line Package (M and N)



Order Number LF156AH, LF155H, LF156H, LF255H,  
LF256H, LF257H, LF355AH, LF356AH,  
LF357AH, LF356BH, LF355H, LF356H,  
LF357H, LM155AH/883, LM155H/883, LM156AH/883,  
LM156H/883, LM157AH/883 or LM157H/883\*  
See NS Package Number H08C

TL/H/5646-29  
Order Number LF355M, LF356M, LF357M, LF355BM,  
LF356BM, LF355BN, LF356BN, LF357BN, LF355N,  
LF356N or LF357N  
See NS Package Number M08A or N08E

\*Available per JM38510/11401 or JM38510/11402

## Application Hints

The LF155/6/7 series are op amps with JFET input devices. These JFETs have large reverse breakdown voltages from gate to source and drain eliminating the need for clamps across the inputs. Therefore large differential input voltages can easily be accommodated without a large increase in input current. The maximum differential input voltage is independent of the supply voltages. However, neither of the input voltages should be allowed to exceed the negative supply as this will cause large currents to flow which can result in a destroyed unit.

Exceeding the negative common-mode limit on either input will force the output to a high state, potentially causing a reversal of phase to the output. Exceeding the negative common-mode limit on both inputs will force the amplifier output to a high state. In neither case does a latch occur since raising the input back within the common-mode range again puts the input stage and thus the amplifier in a normal operating mode.

Exceeding the positive common-mode limit on a single input will not change the phase of the output however, if both inputs exceed the limit, the output of the amplifier will be forced to a high state.

These amplifiers will operate with the common-mode input voltage equal to the positive supply. In fact, the common-mode voltage can exceed the positive supply by approximately 100 mV independent of supply voltage and over the full operating temperature range. The positive supply can therefore be used as a reference on an input as, for example, in a supply current monitor and/or limiter.

Precautions should be taken to ensure that the power supply for the integrated circuit never becomes reversed in polarity or that the unit is not inadvertently installed backwards in a socket as an unlimited current surge through the resulting forward diode within the IC could cause fusing of the internal conductors and result in a destroyed unit.


All of the bias currents in these amplifiers are set by FET current sources. The drain currents for the amplifiers are therefore essentially independent of supply voltage.

As with most amplifiers, care should be taken with lead dress, component placement and supply decoupling in order to ensure stability. For example, resistors from the output to an input should be placed with the body close to the input to minimize "pickup" and maximize the frequency of the feedback pole by minimizing the capacitance from the input to ground.

A feedback pole is created when the feedback around any amplifier is resistive. The parallel resistance and capacitance from the input of the device (usually the inverting input) to ac ground set the frequency of the pole. In many instances the frequency of this pole is much greater than the expected 3 dB frequency of the closed loop gain and consequently there is negligible effect on stability margin. However, if the feedback pole is less than approximately six times the expected 3 dB frequency a lead capacitor should be placed from the output to the input of the op amp. The value of the added capacitor should be such that the RC time constant of this capacitor and the resistance it parallels is greater than or equal to the original feedback pole time constant.


## Typical Circuit Connections

**V<sub>OS</sub>** Adjustment




- V<sub>OS</sub> is adjusted with a 25k potentiometer
- The potentiometer wiper is connected to V<sup>+</sup>
- For potentiometers with temperature coefficient of 100 ppm/°C or less the additional drift with adjust is  $\approx 0.5 \mu\text{V}/\text{C}/\text{mV}$  of adjustment
- Typical overall drift:  $5 \mu\text{V}/\text{C} \pm (0.5 \mu\text{V}/\text{C}/\text{mV of adj.})$

**Driving Capacitive Loads**



- \*LF155/6 R=5k  
LF157 R=1.25k
- Due to a unique output stage design, these amplifiers have the ability to drive large capacitive loads and still maintain stability.  $C_L(\text{MAX}) \approx 0.01 \mu\text{F}$ .
- Overshoot  $\leq 20\%$
- Settling time ( $t_s$ )  $\approx 5 \mu\text{s}$


**LF157. A Large Power BW Amplifier**



TL/H/5646-15  
For distortion  $\leq 1\%$  and a 20 Vp-p V<sub>OUT</sub> swing, power bandwidth is: 500 kHz.

## Typical Applications




**Settling Time Test Circuit**




- Settling time is tested with the LF155/6 connected as unity gain inverter and LF157 connected for  $A_v = -5$
- FET used to isolate the probe capacitance
- Output = 10V step
- $A_v = -5$  for LF157

TL/H/5646-16

**Large Signal inverter Output, VOUT (from Settling Time Circuit)**



**Low Drift Adjustable Voltage Reference**




- $\Delta V_{OUT}/\Delta T = \pm 0.002\text{%/}^{\circ}\text{C}$
- All resistors and potentiometers should be wire-wound
- P1: drift adjust
- P2:  $V_{OUT}$  adjust
- Use LF155 for
  - Low  $I_B$
  - Low drift
  - Low supply current

TL/H/5646-20

## Typical Applications (Continued)


### Fast Logarithmic Converter



- Dynamic range:  $100 \mu\text{A} \leq I_i \leq 1 \text{ mA}$  (5 decades),  $|V_O| = 1\text{V}/\text{decade}$
- Transient response:  $3 \mu\text{s}$  for  $\Delta I_i = 1 \text{ decade}$
- C1, C2, R2, R3: added dynamic compensation
- Vos adjust the LF156 to minimize quiescent error
- R<sub>T</sub>: Tel Labs type Q81 + 0.3%/ $^{\circ}\text{C}$

$$|V_{\text{OUT}}| = \left[ 1 + \frac{R_2}{R_T} \right] \frac{kT}{q} \ln V_i \left[ \frac{R_f}{V_{\text{REF}} R_i} \right] = \log V_i \frac{1}{R_f I_r} R_2 = 15.7\text{K}, R_T = 1\text{k}, 0.3\%/\text{ }^{\circ}\text{C} \text{ (for temperature compensation)}$$


### Precision Current Monitor



- $V_O = 5 R_1 / R_2$  ( $\text{V/mA}$  of  $I_S$ )
- R1, R2, R3: 0.1% resistors
- Use LF155 for
  - Common-mode range to supply range
  - Low  $I_B$
  - Low  $V_{\text{OS}}$
  - Low Supply Current

TL/H/5646-31

### 8-Bit D/A Converter with Symmetrical Offset Binary Operation




- R1, R2 should be matched within  $\pm 0.05\%$
- Full-scale response time:  $3 \mu\text{s}$

$E_O$	B1	B2	B3	B4	B5	B6	B7	B8	Comments
+ 9.920	1	1	1	1	1	1	1	1	Positive Full-Scale
+ 0.040	1	0	0	0	0	0	0	0	(+) Zero-Scale
- 0.040	0	1	1	1	1	1	1	1	(-) Zero-Scale
- 9.920	0	0	0	0	0	0	0	0	Negative Full-Scale



## Typical Applications (Continued)

**High Impedance, Low Drift Instrumentation Amplifier**




TL/H/5646-26

- $V_{OUT} = \frac{R3}{R} \left[ \frac{2R2}{R1} + 1 \right] \Delta V, V^- + 2V \leq V_{IN} \text{ common-mode} \leq V^+$
- System V<sub>OS</sub> adjusted via A2 V<sub>OS</sub> adjust
- Trim R3 to boost up CMRR to 120 dB. Instrumentation amplifier resistor array recommended for best accuracy and lowest drift

## Typical Applications (Continued)

### Fast Sample and Hold



TL/H/5646-33

- Both amplifiers (A1, A2) have feedback loops individually closed with stable responses (overshoot negligible)
- Acquisition time  $T_A$  estimated by:


$$T_A \approx \left[ \frac{2R_{ON}V_{IN}C_1}{S_r} \right]^{1/2} \text{ provided that:}$$

$$V_{IN} < 2\pi S_r R_{ON} C_h \text{ and } T_A > \frac{V_{IN} C_h}{|I_{OUT(MAX)}|}, R_{ON} \text{ is of SW1}$$

$$\text{If inequality not satisfied: } T_A \approx \frac{V_{IN} C_h}{20 \text{ mA}}$$

- LF156 develops full  $S_r$  output capability for  $V_{IN} \geq 1V$
- Addition of SW2 improves accuracy by putting the voltage drop across SW1 inside the feedback loop
- Overall accuracy of system determined by the accuracy of both amplifiers, A1 and A2

### High Accuracy Sample and Hold




TL/H/5646-27

- By closing the loop through A2, the  $V_{OUT}$  accuracy will be determined uniquely by A1. No  $V_{OS}$  adjust required for A2.
- $T_A$  can be estimated by same considerations as previously but, because of the added propagation delay in the feedback loop (A2) the overshoot is not negligible.
- Overall system slower than fast sample and hold
- R1,  $C_C$ : additional compensation
- Use LF156 for
  - Fast settling time
  - Low  $V_{OS}$

## Typical Applications (Continued)

**High Q Band Pass Filter**



TL/H/5646-28


- By adding positive feedback (R2)  
Q increases to 40

$$\bullet f_{BP} = 100 \text{ kHz}$$

$$\frac{V_{OUT}}{V_{IN}} = 10\sqrt{Q}$$

- Clean layout recommended
- Response to a 1 Vp-p tone burst:  
300 μs

**High Q Notch Filter**



TL/H/5646-34

- $2R1 = R = 10 \text{ M}\Omega$
- $2C = C1 = 300 \text{ pF}$


• Capacitors should be matched to obtain high Q

- $f_{NOTCH} = 120 \text{ Hz}$ , notch =  $-55 \text{ dB}$ ,  $Q > 100$


- Use LF155 for

- Low  $I_B$



- Low supply current



## Physical Dimensions inches (millimeters)




**Metal Can Package (H)**  
 Order Number LF156AH, LF155H, LF156H, LF255H, LF256H, LF257H, LF355AH, LF356AH, LF357AH, LF356BH,  
 LF355H, LF356H or LF357H  
 NS Package Number H08C



**Small Outline Package (M)**  
 Order Number LF355M, LF356M, LF357M, LF355BM or LF356BM  
 NS Package Number M08A

## LF155/LF156/LF157 Series Monolithic JFET Input Operational Amplifiers

### Physical Dimensions inches (millimeters) (Continued)



N08E (REV F)

**Molded Dual-In-Line Package (N)**  
Order Number LF355N, LF356N, LF357N, LF355BN, LF356BN, LF357BN  
NS Package Number N08E

#### LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



**National Semiconductor Corporation**  
1111 West Bardin Road  
Arlington, TX 76017  
Tel: 1(800) 272-9959  
Fax: 1(800) 737-7018

**National Semiconductor Europe**  
Fax: (+49) 0-180-530 85 86  
Email: [cnjwge@tevm2.nsc.com](mailto:cnjwge@tevm2.nsc.com)  
Deutsch Tel: (+49) 0-180-530 85 85  
English Tel: (+49) 0-180-532 78 32  
Français Tel: (+49) 0-180-532 93 58  
Italiano Tel: (+49) 0-180-534 16 80

**National Semiconductor Hong Kong Ltd.**  
13th Floor, Straight Block,  
Ocean Centre, 5 Canton Rd.  
Tsimshatsui, Kowloon  
Hong Kong  
Tel: (852) 2737-1600  
Fax: (852) 2736-9960

**National Semiconductor Japan Ltd.**  
Tel: 81-043-299-2309  
Fax: 81-043-299-2408

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.