


MBR870L - MBR8100L

8.0A SCHOTTKY BARRIER RECTIFIER

Features

- Schottky Barrier Chip
- Guard Ring Die Construction for Transient Protection
- Low Power Loss, High Efficiency
- High Surge Capability
- High Current Capability and Low Forward Voltage Drop
- For Use in Low Voltage, High Frequency Inverters, Free Wheeling, and Polarity Protection Application
- Plastic Material: UL Flammability Classification Rating 94V-0



Pin 2 **0**-

TO-220AC Dim Min Max Α 14.22 15.88 В 9.65 10.67 С 2.54 3.43 D 5.84 6.86 Ε 6.35 G 12.70 14.73 J 0.51 1.14 Κ 3.53Ø 4.09Ø L 3.56 4.83 M 1.14 1.40 0.30 0.64 Ν Р 2.03 2.92 R 4.83 5.33 All Dimensions in mm

Mechanical Data

· Case: Molded Plastic

Terminals: Plated Leads Solderable per
 MIL STD 200, Mathed 200

MIL-STD-202, Method 208
Polarity: See Diagram

Weight: 2.24 grams (approx.)

Mounting Position: AnyMarking: Type Number

Maximum Ratings and Electrical Characteristics @ T_A = 25°C unless otherwise specified

Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristic	Symbol	MBR 870L	MBR 880L	MBR 890L	MBR 8100L	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V _{RRM} V _{RWM} V _R	70	80	90	100	٧
RMS Reverse Voltage	V _{R(RMS)}	49	56	63	70	٧
Average Rectified Output Current (Note 1) @ T _C = 125°C	Io	8.0				А
Non-Repetitive Peak Forward Surge Current, 8.3ms single half sine-wave superimposed on rated load (JEDEC Method)	I _{FSM}	230				А
Repetitive Peak Forward Surge Current @ $t \le 5.0 \mu s$	I _{FRM}	850				Α
Forward Voltage Drop	V _{FM}	0.72 0.58				٧
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	I _{RM}	0.55 7.0				mA
Typical Junction Capacitance (Note 2)	Cj	350				pF
Typical Thermal Resistance Junction to Case (Note 1)	R ₀ JC	2.0				K/W
Voltage Rate of Change (Rated V _R)	dV/dt	10,000				V/µs
Operating and Storage Temperature Range	T _j , T _{STG}	-55 to +175				°C

Notes: 1. Thermal resistance junction to case mounted on heatsink.

2. Measured at 1.0MHz and applied reverse voltage of 4.0V DC.

