


# The RF Line 152-Channel (1000 MHz) CATV Line Extender Amplifier

- Specified for 152-Channel Performance
- Broadband Power Gain — @  $f = 40\text{--}1000\text{ MHz}$   
 $G_p = 24\text{ dB (Typ)}$
- Broadband Noise Figure  
 $NF = 8\text{ dB (Max) @ } 1000\text{ MHz}$
- Superior Gain, Return Loss and DC Current Stability with Temperature
- All Gold Metallization
- 7 GHz  $f_T$  Ion-Implanted Transistors

**MHW9242**

**24 dB GAIN  
1000 MHz  
152-CHANNEL  
CATV AMPLIFIER**



**CASE 714-06, STYLE 1**

## MAXIMUM RATINGS

Rating	Symbol	Value	Unit
RF Voltage Input (Single Tone)	$V_{in}$	+55	dBmV
DC Supply Voltage	$V_{CC}$	+28	Vdc
Operating Case Temperature Range	$T_C$	-20 to +100	°C
Storage Temperature Range	$T_{stg}$	-40 to +100	°C

## ELECTRICAL CHARACTERISTICS ( $V_{CC} = 24\text{ Vdc}$ , $T_C = +30^\circ\text{C}$ , 75 $\Omega$ system unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
Frequency Range	BW	40	—	1000	MHz
Power Gain	$G_p$	50 MHz 23.2	24	24.8	dB
		1000 MHz 24	25	27	
Slope	S	0	1	2.5	dB
Gain Flatness (40-1000 MHz, Peak-to-Valley)	—	—	0.5	1.0	dB
Return Loss — Input/Output ( $Z_O = 75\text{ Ohms}$ )	IRL/ORL	@ 40 MHz 20	—	—	dB
		@ $f > 40\text{ MHz}$ (Derate) —	—	0.01	dB/MHz
Composite Second Order ( $V_{out} = +38\text{ dBmV/ch.}$ , Worst Case)	$CSO_{152}$	—	-65	-59	dBc
Cross Modulation Distortion @ Ch 2 ( $V_{out} = +38\text{ dBmV/ch.}$ , FM = 55 MHz)	$XMD_{152}$	—	-64	-59	dBc
Composite Triple Beat ( $V_{out} = +38\text{ dBmV/ch.}$ , Worst Case)	$CTB_{152}$	—	-61	-58	dBc
Noise Figure	NF	50 MHz —	-5.0	5.5	dB
		1000 MHz —	-7.0	8.0	
DC Current	$I_{DC}$	280	320	350	mA

