



44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

## NTE7110 Integrated Circuit 3 Channel Analog Switch

### Description:

The NTE7110 is an integrated circuit in a 16-Lead DIP type package designed for use as an electronic switch in VCR and audio signal processing applications. This device contains three channel two input switch circuits with each switch being controlled independently.

### Features:

- Low Offset Voltage at Output: 5mV Typ
- Low Switching Noise
- Wide Dynamic Range
- Wide Frequency Range: 40MHz Typ
- Low Crosstalk
- High Speed Response: 0.2 $\mu$ s Typ
- Low Power Consumption

### Absolute Maximum Ratings:

Supply Voltage, $V_{CC}$ .....	14V
Power Dissipation, $P_D$ .....	1000mw
Derate Above 25°C .....	10mW/°C
Operating Temperature Range, $T_{opr}$ .....	-20° to +75°C
Storage Temperature Range, $T_{stg}$ .....	-40° to +125°C

### Recommended Operating Condition:

Supply Voltage Range, $V_{CC}$ .....	4.5V to 13V
--------------------------------------	-------------

### Electrical Characteristics: ( $T_A = +25^\circ C$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current	$I_{CC1}$	$V_{CC} = 9V$	5.2	7.1	9.0	mA
	$I_{CC2}$	$V_{CC} = 5V$	2.4	3.4	4.4	mA
Voltage Gain	$G_{V1}$	$f = 1MHz, V_{in} = 0.5V_{P-P}$	-0.6	-0.1	0.4	dB
	$G_{V2}$	$f = 10MHz, V_{in} = 0.5V_{P-P}$	-0.6	-0.1	0.4	dB

**Electrical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
2 <sup>nd</sup> Harmonic Distortion	HD	f = 5MHz, $V_{in} = 4.5\text{V}_{P-P}$ , $R_L = 2\text{k}\Omega$	—	-60	-50	dB
Switch Crosstalk	CT <sub>sw</sub>	f = 5MHz, $V_{in} = 0.5\text{V}_{P-P}$	—	-70	-60	dB
Channel Crosstalk	CT <sub>ch</sub>	f = 5MHz, $V_{in} = 0.5\text{V}_{P-P}$	—	-70	-60	dB
Output DC Offset Voltage	V <sub>os</sub>		-10	0	+10	mV
Switch Threshold Voltage	V <sub>th1</sub>	$V_{CC} = 5\text{V}$	1.3	—	2.3	V
	V <sub>th2</sub>	$V_{CC} = 9\text{V}$	1.7	—	2.7	V
	V <sub>th3</sub>	$V_{CC} = 12\text{V}$	2.0	—	3.0	V
Input Impedance	Z <sub>in</sub>		—	20	—	k $\Omega$

Pin Connection Diagram

