

LOW DROP POWER SCHOTTKY RECTIFIER

MAIN PRODUCTS CHARACTERISTICS

I_{F(AV)}	2 x 7.5 A
V_{RRM}	30 V
T_j (max)	150 °C
V_F (max)	0.39 V


FEATURES AND BENEFITS

- VERY SMALL CONDUCTION LOSSES
- NEGLIGIBLE SWITCHING LOSSES
- EXTREMELY FAST SWITCHING
- LOW FORWARD VOLTAGE DROP
- HIGH AVALANCHE CAPABILITY
- LOW THERMAL RESISTANCE
- AVALANCHE CAPABILITY SPECIFIED

DESCRIPTION

Dual center tab Schottky rectifier suited for switch Mode Power Supply and high frequency DC to DC converters.

Package in DPAK, this device is intended for use in low voltage, high frequency inverters, free-wheeling and polarity protection applications.



ABSOLUTE RATINGS (limiting values, per diode)

Symbol	Parameter		Value	Unit
V _{RRM}	Repetitive peak reverse voltage		30	V
I _{F(RMS)}	RMS forward current		10	A
I _{F(AV)}	Average forward current	T _c = 140°C δ = 0.5	Per diode 7.5 Per device 15	A
I _{FSM}	Surge non repetitive forward current	tp = 10 ms sinusoidal	75	A
I _{RRM}	Peak repetitive reverse current	tp=2 μs square F=1kHz	1	A
P _{ARM}	Repetitive peak avalanche power	tp = 1μs T _j = 25°C	2800	W
T _{stg}	Storage temperature range		- 65 to + 175	°C
T _j	Maximum operating junction temperature *		150	°C
dV/dt	Critical rate of rise reverse voltage		10000	V/μs

* : $\frac{dP_{tot}}{dT_j} < \frac{1}{R_{th}(j-a)}$ thermal runaway condition for a diode on its own heatsink

STPS15L30CB

THERMAL RESISTANCES

Symbol	Parameter		Value	Unit
$R_{th(j-c)}$	Junction to case	Per diode Total	4 2.4	°C/W
$R_{th(c)}$	Coupling		0.7	

When the diodes 1 and 2 are used simultaneously :

$$\Delta T_j(\text{diode 1}) = P(\text{diode 1}) \times R_{th(j-c)}(\text{Per diode}) + P(\text{diode 2}) \times R_{th(c)}$$

STATIC ELECTRICAL CHARACTERISTICS (per diode)

Symbol	Parameter	Tests Conditions		Min.	Typ.	Max.	Unit
I_R^*	Reverse leakage current	$T_j = 25^\circ\text{C}$	$V_R = V_{RRM}$			1	mA
		$T_j = 125^\circ\text{C}$			70	140	mA
V_F^*	Forward voltage drop	$T_j = 25^\circ\text{C}$	$I_F = 7.5 \text{ A}$			0.48	V
		$T_j = 125^\circ\text{C}$	$I_F = 7.5 \text{ A}$		0.34	0.39	
		$T_j = 25^\circ\text{C}$	$I_F = 12 \text{ A}$			0.53	
		$T_j = 125^\circ\text{C}$	$I_F = 12 \text{ A}$		0.40	0.47	
		$T_j = 25^\circ\text{C}$	$I_F = 15 \text{ A}$			0.57	
		$T_j = 125^\circ\text{C}$	$I_F = 15 \text{ A}$		0.44	0.51	

Pulse test : * $t_p = 380 \mu\text{s}$, $\delta < 2\%$

To evaluate the conduction losses use the following equation :

$$P = 0.27 \times I_{F(AV)} + 0.016 I_{F(RMS)}^2$$

Fig. 1: Conduction losses versus average current.




Fig. 2: Average forward current versus ambient temperature ($\delta = 0.5$).




Fig. 3: Normalized avalanche power derating versus pulse duration.




Fig. 4: Normalized avalanche power derating versus junction temperature.




Fig. 5: Non repetitive surge peak forward current versus overload duration (maximum values).




Fig. 6: Relative variation of thermal impedance junction to case versus pulse duration.




Fig. 7: Reverse leakage current versus reverse voltage applied (typical values).




Fig. 8: Junction capacitance versus reverse voltage applied (typical values).




Fig. 9: Forward voltage drop versus forward current.







Fig. 10: Thermal resistance junction to ambient versus copper surface area under tab (epoxy printed board FR4, Cu = 35µm).



PACKAGE MECHANICAL DATA
DPAK



FOOTPRINT (dimensions in mm)



Ordering type	Marking	Package	Weight	Base qty	Delivery mode
STPS15L30CB	S15L30C	DPAK	0.30 g	75	Tube
STPS15L30CB-TR	S15L30C	DPAK	0.30 g	2500	Tape & reel

■ EPOXY MEETS UL94,V0

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics
 © 2003 STMicroelectronics - Printed in Italy - All rights reserved.
 STMicroelectronics GROUP OF COMPANIES
 Australia - Brazil - Canada - China - Finland - France - Germany
 Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore
 Spain - Sweden - Switzerland - United Kingdom - United States.

<http://www.st.com>

