

SANYO	No.915C	2SB888
		PNP Epitaxial Planar Silicon Darlington Transistor

Driver Applications

Applications

- . Motor drivers, printer hammer drivers, relay drivers, voltage regulator control

Features

- . High DC current gain (5000 or greater).
- . Large current capacity and wide ASO.
- . Low saturation voltage ($V_{CE(sat)} = -0.8V$ typ).


Absolute Maximum Ratings at $T_a = 25^\circ C$

Collector to Base Voltage	V_{CBO}	-80	V	unit
Collector to Emitter Voltage	V_{CEO}	-50	V	
Emitter to Base Voltage	V_{EBO}	-10	V	
Collector Current	I_C	-0.7	A	
Collector Current(Pulse)	I_{CP}	-2	A	
Allowable Collector Dissipation	P_C	600	mW	
Junction Temperature	T_j	150	$^\circ C$	
Storage Temperature	T_{stg}	-55 to +150	$^\circ C$	


Electrical Characteristics at $T_a = 25^\circ C$









		min	typ	max	unit
Collector Cutoff Current	I_{CBO} $V_{CB} = -40V, I_E = 0$			-0.1	μA
Emitter Cutoff Current	I_{EBO} $V_{EB} = -8V, I_C = 0$			-0.1	μA
DC Current Gain	$h_{FE(1)}$ $V_{CE} = -2V, I_C = -50mA$	5000			
	$h_{FE(2)}$ $V_{CE} = -2V, I_C = -500mA$	3000			
Gain-Bandwidth Product	f_T $V_{CE} = -5V, I_C = -50mA$		170		MHz
Output Capacitance	c_{ob} $V_{CB} = -10V, f = 1MHz$		16		pF
C-E Saturation Voltage	$V_{CE(sat)}$ $I_C = -100mA, I_B = -0.1mA$	-0.8	-1.2		V
B-E Saturation Voltage	$V_{BE(sat)}$ $I_C = -100mA, I_B = -0.1mA$	-1.3	-2.0		V
C-B Breakdown Voltage	$V_{(BR)CBO}$ $I_C = -10\mu A, I_E = 0$	-80			V
C-E Breakdown Voltage	$V_{(BR)CEO}$ $I_C = -1mA, R_{BE} = \infty$	-50			V
E-B Breakdown Voltage	$V_{(BR)EBO}$ $I_E = -10\mu A, I_C = 0$	-10			V

Electrical Connection



Package Dimensions 2003A
(unit: mm)





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.