



No.4634

2SK1839

N-Channel Enhancement MOS Silicon FET

Analog Switch Applications

Features

- Very small-sized package permitting 2SK1839-applied sets to be made small and slim.
- Large $|Y_{fs}|$.
- Enhancement type.
- Low ON resistance.

Absolute Maximum Ratings at Ta = 25°C


			unit
Drain-to-Source Voltage	V_{DSS}	30	V
Gate-to-Source Voltage	V_{GSS}	± 12	V
Drain Current(DC)	I_D	100	mA
Drain Current(Pulse)	I_{DP}	300	mA
Allowable Power Dissipation	P_D	150	mW
Channel Temperature	T_{ch}	125	°C
Storage Temperature	T_{stg}	-55 to +125	°C

Electrical Characteristics at Ta = 25°C



			min	typ	max	unit
D-S Breakdown Voltage	$V_{(BR)DSS}$	$I_D = 10\mu A, V_{GS} = 0$	30			V
Drain Current	I_{DSS}	$V_{DS} = 15V, V_{GS} = 0$			1	μA
Gate Cutoff Current	I_{GSS}	$V_{GS} = \pm 10V, V_{DS} = 0$		0.01	± 10	nA
Cutoff Voltage	$V_{GS(off)}$	$V_{DS} = 10V, I_D = 100\mu A$	0.3	0.9	1.5	V
Forward Transfer Admittance	$ Y_{fs} $	$V_{DS} = 10V, I_D = 50mA, f = 1kHz$	25	50		mS
Static Drain-to-Source ON-State Resistance	$R_{DS(on)}$	$V_{GS} = 10V, I_D = 10mA$		15	25	Ω
Input Capacitance	C_{iss}	$V_{DS} = 10V, V_{GS} = 0, f = 1MHz$		12		pF
Output Capacitance	C_{oss}	$V_{DS} = 10V, V_{GS} = 0, f = 1MHz$		4		pF
Reverse Transfer Capacitance	C_{rss}	$V_{DS} = 10V, V_{GS} = 0, f = 1MHz$		0.4		pF

Marking : JJ









Electrical Connection




Package Dimensions 2057A
(unit : mm)



SANYO : MCP





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.