

MBR830 - MBR860

8.0A SCHOTTKY BARRIER RECTIFIER

Features

- Schottky Barrier Chip
- Guard Ring Die Construction for Transient Protection
- Low Power Loss, High Efficiency
- High Surge Capability
- High Current Capability and Low Forward Voltage Drop
- For Use in Low Voltage, High Frequency Inverters, Free Wheeling, and Polarity Protection Application
- Plastic Material: UL Flammability Classification Rating 94V-0

Pin 2 O

TO-220AC Dim Min Max Α 14.22 15.88 В 9.65 10.67 С 3.43 2.54 D 5.84 6.86 Ε 6.35 G 12.70 14.73 J 0.51 1.14 Κ 3.53Ø 4.09Ø L 3.56 4.83 M 1.14 1.40 0.30 0.64 Ν Р 2.03 2.92 5.33 R 4.83 All Dimensions in mm

Mechanical Data

Case: Molded Plastic

Terminals: Plated Leads Solderable per

MIL-STD-202, Method 208

Polarity: See Diagram

Weight: 2.24 grams (approx.)

Mounting Position: Any

Marking: Type Number

Maximum Ratings and Electrical Characteristics @ TA = 25°C unless otherwise specified

Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristic	Symbol	MBR 830	MBR 835	MBR 840	MBR 845	MBR 850	MBR 860	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V _{RRM} V _{RWM} V _R	30	35	40	45	50	60	V
RMS Reverse Voltage	V _{R(RMS)}	21	24.5	28	31.5	35	42	٧
Average Rectified Output Current (Note 1) @ T _C = 125°C	; lo	8.0						А
Non-Repetitive Peak Forward Surge Current 8.3ms single half sine-wave superimposed on rated load (JEDEC Method)	I _{FSM}	150					А	
Repetitive Peak Reverse Surge Current @ t ≤ 2.0µ	s I _{RRM}	1.0					Α	
Forward Voltage Drop	C V _{FM}	0.57 0.70 0.84				0.	70 80 95	V
Peak Reverse Current @ $T_C = 25^{\circ}$ at Rated DC Blocking Voltage @ $T_C = 125^{\circ}$		0.1 15					mA	
Typical Junction Capacitance (Note 2)	Cj	250					pF	
Typical Thermal Resistance Junction to Case (Note 1)	R _θ JC	3.0					K/W	
Voltage Rate of Change (Rated V _R)	dV/dt	1000					V/μs	
Operating and Storage Temperature Range	T _{j,} T _{STG}	-65 to +150						°C

Notes: 1. Thermal resistance junction to case mounted on heatsink.

2. Measured at 1.0MHz and applied reverse voltage of 4.0V DC.

