

Low-Voltage CMOS Octal Transparent Latch Flow Through Pinout With 5V-Tolerant Inputs and Outputs (3-State, Non-Inverting)


The MC74LCX573 is a high performance, non-inverting octal transparent latch operating from a 2.7 to 3.6V supply. High impedance TTL compatible inputs significantly reduce current loading to input drivers while TTL compatible outputs offer improved switching noise performance. A VI specification of 5.5V allows MC74LCX573 inputs to be safely driven from 5V devices.

The MC74LCX573 contains 8 D-type latches with 3-state standard outputs. When the Latch Enable (LE) input is HIGH, data on the Dn inputs enters the latches. In this condition, the latches are transparent, i.e., a latch output will change state each time its D input changes. When LE is LOW, the latches store the information that was present on the D inputs a setup time preceding the HIGH-to-LOW transition of <u>LE</u>. The 3-state <u>stan</u>dard outputs are controlled by the Output Enable (<u>OE</u>) input. When OE is LOW, the standard outputs are enabled. When OE is HIGH, the standard outputs are in the high impedance state, but this does not interfere with new data entering into the latches. The LCX573 flow through design facilitates easy PC board layout.

- Designed for 2.7 to 3.6V V_{CC} Operation
- 5V Tolerant Interface Capability With 5V TTL Logic
- · Supports Live Insertion and Withdrawal
- IOFF Specification Guarantees High Impedance When VCC = 0V
- LVTTL Compatible
- LVCMOS Compatible
- 24mA Balanced Output Sink and Source Capability
- Near Zero Static Supply Current in All Three Logic States (10μA) Substantially Reduces System Power Requirements
- Latchup Performance Exceeds 500mA
- ESD Performance: Human Body Model >2000V; Machine Model >200V








3-State Latch Outputs

11/96

00-07

LOGIC DIAGRAM



	INPUTS		OUTPUTS	
OE	LE	Dn	On	OPERATING MODE
L	H H	HL	H L	Transparent (Latch Disabled); Read Latch
L	L	h I	H L	Latched (Latch Enabled) Read Latch
L	L	Х	NC	Hold; Read Latch
Н	L	Х	Z	Hold; Disabled Outputs
H H	H H	HL	Z Z	Transparent (Latch Disabled); Disabled Outputs
H H	L	h I	Z Z	Latched (Latch Enabled); Disabled Outputs

H = High Voltage Level; h = High Voltage Level One Setup Time Prior to the Latch Enable High–to–Low Transition; L = Low Voltage Level; I = Low Voltage Level One Setup Time Prior to the Latch Enable High–to–Low Transition; NC = No Change, State Prior to the Latch Enable High–to–Low Transition; X = High or Low Voltage Level or Transitions are Acceptable; Z = High Impedance State; For I_{CC} Reasons DO NOT FLOAT Inputs

ABSOLUTE MAXIMUM RATINGS*

Symbol	Parameter	Value	Condition	Unit
VCC	DC Supply Voltage	-0.5 to +7.0		V
VI	DC Input Voltage	$-0.5 \le V_{l} \le +7.0$		V
VO	DC Output Voltage	$-0.5 \le V_O \le +7.0$	Output in 3–State	V
		$-0.5 \le V_{O} \le V_{CC} + 0.5$	Note 1.	V
liк	DC Input Diode Current	-50	V _I < GND	mA
юк	DC Output Diode Current	-50	V _O < GND	mA
		+50	VO > ACC	mA
IO	DC Output Source/Sink Current	±50		mA
ICC	DC Supply Current Per Supply Pin	±100		mA
I _{GND}	DC Ground Current Per Ground Pin	±100		mA
T _{STG}	Storage Temperature Range	-65 to +150		°C

* Absolute maximum continuous ratings are those values beyond which damage to the device may occur. Exposure to these conditions or conditions beyond those indicated may adversely affect device reliability. Functional operation under absolute-maximum-rated conditions is not implied.
1. Output in HIGH or LOW State. I_O absolute maximum rating must be observed.

RECOMMENDED OPERATING CONDITIONS

Symbol	Parameter	Min	Тур	Max	Unit
V _{CC}	Supply Voltage Operating Data Retention Only	2.0 1.5	3.3 3.3	3.6 3.6	V
VI	Input Voltage	0		5.5	V
VO	Output Voltage (HIGH or LOW State) (3–State)	0 0		V _{CC} 5.5	V
IОН	HIGH Level Output Current, $V_{CC} = 3.0V - 3.6V$			-24	mA
lol	LOW Level Output Current, $V_{CC} = 3.0V - 3.6V$			24	mA
I _{ОН}	HIGH Level Output Current, $V_{CC} = 2.7V - 3.0V$			-12	mA
IOL	LOW Level Output Current, $V_{CC} = 2.7V - 3.0V$			12	mA
Т _А	Operating Free-Air Temperature	-40		+85	°C
Δt/ΔV	Input Transition Rise or Fall Rate, V _{IN} from 0.8V to 2.0V, V _{CC} = 3.0V	0		10	ns/V

DC ELECTRICAL CHARACTERISTICS

			T _A = −40°C to +85°C		
Symbol	Characteristic	Condition	Min	Max	Unit
VIH	HIGH Level Input Voltage (Note 2.)	$2.7V \le V_{CC} \le 3.6V$	2.0		V
VIL	LOW Level Input Voltage (Note 2.)	$2.7 \text{V} \leq \text{V}_{CC} \leq 3.6 \text{V}$		0.8	V
VOH	HIGH Level Output Voltage	$2.7V \leq V_{CC} \leq 3.6V; \ I_{OH} = -100 \mu A$	V _{CC} – 0.2		V
		$V_{CC} = 2.7V; I_{OH} = -12mA$	2.2		
		$V_{CC} = 3.0V; I_{OH} = -18mA$	2.4		
		$V_{CC} = 3.0V; I_{OH} = -24mA$	2.2		
VOL	LOW Level Output Voltage	$2.7V \leq V_{CC} \leq 3.6V; \ I_{OL} = 100 \mu A$		0.2	V
		V _{CC} = 2.7V; I _{OL} = 12mA		0.4	
		V _{CC} = 3.0V; I _{OL} = 16mA		0.4	
		V _{CC} = 3.0V; I _{OL} = 24mA		0.55	

2. These values of VI are used to test DC electrical characteristics only.

DC ELECTRICAL CHARACTERISTICS (continued)

			T _A = −40°C to +85°C		
Symbol	Characteristic	Condition	Min	Max	Unit
Ц	Input Leakage Current	$2.7V \leq V_{CC} \leq 3.6V; \ 0V \leq V_I \leq 5.5V$		±5.0	μΑ
loz	3-State Output Current	$\begin{array}{c} 2.7 \leq V_{CC} \leq 3.6 \text{V}; \ 0 \text{V} \leq \text{V}_{O} \leq 5.5 \text{V}; \\ \text{V}_{I} = \text{V}_{IH} \ \text{or} \ \text{V} \ \text{IL} \end{array}$		±5.0	μΑ
IOFF	Power–Off Leakage Current	$V_{CC} = 0V; V_I \text{ or } V_O = 5.5V$		10	μA
ICC	Quiescent Supply Current	$2.7 \leq V_{CC} \leq 3.6 \text{V}; \ \text{V}_{I} = \text{GND} \ \text{or} \ \text{V}_{CC}$		10	μΑ
		$2.7 \leq V_{CC} \leq 3.6 \textrm{V}; \ 3.6 \leq \textrm{V}_{I} \ \textrm{or} \ \textrm{V}_{O} \leq 5.5 \textrm{V}$		±10	μA
Δlcc	Increase in I _{CC} per Input	$2.7 \leq V_{CC} \leq 3.6 \text{V}; \text{ V}_{IH} = V_{CC} - 0.6 \text{V}$		500	μA

AC CHARACTERISTICS ($t_R = t_F = 2.5ns$; $C_L = 50pF$; $R_L = 500\Omega$)

				Lin	nits		
				T _A = -40°0	C to +85°C		
			V _{CC} = 3.0	0V to 3.6V	VCC =	= 2.7V	
Symbol	Parameter	Waveform	Min	Max	Min	Max	Unit
^t PLH ^t PHL	Propagation Delay Dn to On	1	1.5 1.5	8.0 8.0	1.5 1.5	9.0 9.0	ns
^t PLH ^t PHL	Propagation Delay LE to On	3	1.5 1.5	8.5 8.5	1.5 1.5	9.5 9.5	ns
^t PZH ^t PZL	Output Enable Time to HIGH and LOW Level	2	1.5 1.5	8.5 8.5	1.5 1.5	9.5 9.5	ns
^t PHZ ^t PLZ	Output Disable Time from HIGH and LOW Level	2	1.5 1.5	6.5 6.5	1.5 1.5	7.0 7.0	ns
t _S	Setup TIme, HIGH or LOW Dn to LE	3	2.5		2.5		ns
t _h	Hold TIme, HIGH or LOW Dn to LE	3	1.5		1.5		ns
t _W	LE Pulse Width, HIGH	3	3.3		3.3		ns
^t OSHL ^t OSLH	Output-to-Output Skew (Note 3.)			1.0 1.0			ns

 Skew is defined as the absolute value of the difference between the actual propagation delay for any two separate outputs of the same device. The specification applies to any outputs switching in the same direction, either HIGH-to-LOW (t_{OSHL}) or LOW-to-HIGH (t_{OSLH}); parameter guaranteed by design.


DYNAMIC SWITCHING CHARACTERISTICS

			T _A = +25°C			
Symbol	Characteristic	Condition	Min	Тур	Max	Unit
VOLP	Dynamic LOW Peak Voltage (Note 4.)	$V_{\mbox{\scriptsize CC}}$ = 3.3V, $C_{\mbox{\scriptsize L}}$ = 50pF, $V_{\mbox{\scriptsize IH}}$ = 3.3V, $V_{\mbox{\scriptsize IL}}$ = 0V		0.8		V
VOLV	Dynamic LOW Valley Voltage (Note 4.)	$V_{\mbox{\scriptsize CC}}$ = 3.3V, $C_{\mbox{\scriptsize L}}$ = 50pF, $V_{\mbox{\scriptsize IH}}$ = 3.3V, $V_{\mbox{\scriptsize IL}}$ = 0V		0.8		V


 Number of outputs defined as "n". Measured with "n-1" outputs switching from HIGH-to-LOW or LOW-to-HIGH. The remaining output is measured in the LOW state.


CAPACITIVE CHARACTERISTICS

Symbol	Parameter	Condition	Typical	Unit
C _{IN}	Input Capacitance	$V_{CC} = 3.3$ V, $V_{I} = 0$ V or V_{CC}	7	pF
COUT	Output Capacitance	$V_{CC} = 3.3V$, $V_I = 0V$ or V_{CC}	8	pF
C _{PD}	Power Dissipation Capacitance	10MHz, V _{CC} = 3.3V, V _I = 0V or V _{CC}	25	pF



WAVEFORM 1 - PROPAGATION DELAYS tR = tF = 2.5ns, 10% to 90%; f = 1MHz; tW = 500ns





WAVEFORM 3 - LE to On PROPAGATION DELAYS, LE MINIMUM PULSE WIDTH, Dn to LE SETUP AND HOLD TIMES $t_R = t_F = 2.5$ ns, 10% to 90%; f = 1MHz; $t_W = 500$ ns except when noted





Figure 1. AC Waveforms




TEST	SWITCH
tPLH, tPHL	Open
tPZL, tPLZ	6V
Open Collector/Drain tPLH and tPHL	6V
^t PZH ^{, t} PHZ	GND

 $C_L = 50 pF$ or equivalent (Includes jig and probe capacitance)


 $R_L = R_1 = 500\Omega$ or equivalent $R_T = Z_{OUT}$ of pulse generator (typically 50 Ω)

Figure 2. Test Circuit





OUTLINE DIMENSIONS



Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and **()** are registered trademarks of Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution; P.O. Box 5405, Denver, Colorado 80217. 1–800–441–2447 JAPAN: Nippon Motorola Ltd.; Tatsumi–SPD–JLDC, 6F Seibu–Butsuryu–Center, 3–14–2 Tatsumi Koto–Ku, Tokyo 135, Japan. 03–81–3521–8315

Mfax™: RMFAX0@email.sps.mot.com – TOUCHTONE 602–244–6609 INTERNET: http://Design–NET.com

٥



