

## NTE491 MOSFET N-Ch, Enhancement Mode High Speed Switch

**Absolute Maximum Ratings:**

Drain-Source Voltage, $V_{DS}$ .....	60V
Drain-Gate Voltage ( $R_{GS} = 1M\Omega$ ), $V_{DGR}$ .....	60V
Gate-Source Voltage, $V_{GS}$ .....	$\pm 40V$
Drain Current, $I_D$	
Continuous .....	200mA
Pulsed .....	500mA
Total Device Dissipation ( $T_A = +25^\circ C$ ), $P_D$ .....	350mW
Derate above $25^\circ C$ .....	2.8mW/ $^\circ C$
Operating Junction Temperature Range, $T_J$ .....	$-55^\circ$ to $+150^\circ C$
Storage Temperature Range, $T_{stg}$ .....	$-55^\circ$ to $+150^\circ C$
Thermal Resistance, Junction-to-Ambient, $R_{th(JA)}$ .....	312.5 $^\circ C/W$
Maximum Lead Temperature (During Soldering, 1/16" from case, 10sec), $T_L$ .....	$+300^\circ C$

**Electrical Characteristics:** ( $T_A = +25^\circ C$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
<b>OFF Characteristics</b>						
Zero-Gate-Voltage Drain Current	$I_{DSS}$	$V_{DS} = 48V, V_{GS} = 0$	-	-	1.0	$\mu A$
		$V_{DS} = 48V, V_{GS} = 0, T_J = +125^\circ C$	-	-	1.0	mA
Drain-Source Breakdown Voltage	$V_{(BR)DSS}$	$V_{GS} = 0, I_D = 10\mu A$	60	-	-	V
Gate-Body Leakage Current, Forward	$I_{GSSF}$	$V_{GSF} = 15V, V_{DS} = 0$	-	-	-10	nA
<b>ON Characteristics (Note 1)</b>						
Gate Threshold Voltage	$V_{GS(Th)}$	$I_D = 1mA, V_{DS} = V_{GS}$	0.8	-	3.0	V
Static Drain-Source ON Resistance	$r_{DS(on)}$	$V_{GS} = 10V, I_D = 500mA$	-	-	5.0	$\Omega$
		$V_{GS} = 4.5V, I_D = 75mA$	-	-	6.0	$\Omega$
Drain-Source ON-Voltage	$V_{DS(on)}$	$V_{GS} = 10V, I_D = 500mA$	-	-	2.5	V
		$V_{GS} = 4.5V, I_D = 75mA$	-	-	0.45	V
ON-State Drain Current	$I_{d(on)}$	$V_{GS} = 4.5V, V_{DS} = 10V$	75	-	-	mA
Forward Transconductance	$g_{fs}$	$V_{DS} = 10V, I_D = 200mA$	100	-	-	$\mu mhos$

Note 1. Pulse Test: Pulse Width  $\leq 300\mu s$ , Duty Cycle  $\leq 2\%$ .

**Electrical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
<b>Dynamic Characteristics</b>						
Input Capacitance	$C_{iss}$	$V_{DS} = 25\text{V}, V_{GS} = 0, f = 1\text{MHz}$	-	-	60	pF
Reverse Transfer Capacitance	$C_{rss}$		-	-	25	pF
Output Capacitance	$C_{oss}$		-	-	5.0	pF
<b>Switching Characteristics</b>						
Turn-On Delay Time	$t_{on}$	$V_{DD} = 15\text{V}, I_D = 500\text{mA}, R_{gen} = 25\Omega, R_L = 25\Omega$	-	-	10	ns
Turn-Off Delay Time	$t_{off}$		-	-	10	ns

