


SB120 - SB160

1.0A SCHOTTKY BARRIER RECTIFIER

Features

- Schottky Barrier Chip
- Guard Ring Die Construction for Transient Protection
- High Current Capability
- Low Power Loss, High Efficiency
- High Surge Current Capability
- For Use in Low Voltage, High Frequency Inverters, Free Wheeling, and Polarity Protection Applications



Mechanical Data

Case: Molded Plastic

Terminals: Plated Leads Solderable per

MIL-STD-202, Method 208

Polarity: Cathode Band

• Weight: 0.34 grams (approx.)

Mounting Position: Any

Marking: Type Number

DO-41					
Dim	Min	Max			
Α	25.4	_			
В	4.06	5.21			
С	0.71	0.864			
D	2.00	2.72			
All Dimensions in mm					


Maximum Ratings and Electrical Characteristics @T_A=25°C unless otherwise specified

Single Phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.


Characteristic	Symbol	SB120	SB130	SB140	SB150	SB160	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	VRRM VRWM VR	20	30	40	50	60	V
RMS Reverse Voltage	VR(RMS)	14	21	28	35	42	V
Average Rectified Output Current (Note 1) @T _L = 100	°C Io	1.0					Α
Non-Repetitive Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method)	IFSM			40			Α
Forward Voltage @I _F = 1	.0A VFM	0.50 0.70			70	V	
	I IDM			0.5 10			mA
Typical Junction Capacitance (Note 2)	Cj	110			8	0	pF
Typical Thermal Resistance Junction to Lead	RθJL	15				K/W	
Typical Thermal Resistance Junction to Ambient (Note 1)	$R_{ heta}$ JA	50				K/W	
Operating and Storage Temperature Range	Тj, Tsтg	-65 to +150					°C

Note: 1. Valid provided that leads are kept at ambient temperature at a distance of 9.5mm from the case.


2. Measured at 1.0 MHz and applied reverse voltage of 4.0V D.C.




T_L, LEAD TEMPERATURE (°C) Fig. 1 Forward Current Derating Curve



V_F, INSTANTANEOUS FORWARD VOLTAGE (V) Fig. 2 Typical Forward Characteristics



NUMBER OF CYCLES AT 60 Hz Fig. 3 Max Non-Repetitive Peak Fwd Surge Current






Fig. 5 Typical Reverse Characteristics

ORDERING INFORMATION

Product No.◆	Package Type	Shipping Quantity		
SB120-T3	DO-41	5000/Tape & Reel		
SB120-TB	DO-41	5000/Tape & Box		
SB120	DO-41	1000 Units/Box		
SB130-T3	DO-41	5000/Tape & Reel		
SB130-TB	DO-41	5000/Tape & Box		
SB130	DO-41	1000 Units/Box		
SB140-T3	DO-41	5000/Tape & Reel		
SB140-TB	DO-41	5000/Tape & Box		
SB140	DO-41	1000 Units/Box		
SB150-T3	DO-41	5000/Tape & Reel		
SB150-TB	DO-41	5000/Tape & Box		
SB150	DO-41	1000 Units/Box		
SB160-T3	DO-41	5000/Tape & Reel		
SB160-TB	DO-41	5000/Tape & Box		
SB160	DO-41	1000 Units/Box		

Won-Top Electronics Co., Ltd (WTE) has checked all information carefully and believes it to be correct and accurate. However, WTE cannot assume any responsibility for inaccuracies. Furthermore, this information does not give the purchaser of semiconductor devices any license under patent rights to manufacturer. WTE reserves the right to change any or all information herein without further notice.

WARNING: DO NOT USE IN LIFE SUPPORT EQUIPMENT. WTE power semiconductor products are not authorized for use as critical components in life support devices or systems without the express written approval.

Won-Top Electronics Co., Ltd.

No. 44 Yu Kang North 3rd Road, Chine Chen Dist., Kaohsiung, Taiwan

Phone: 886-7-822-5408 or 886-7-822-5410

Fax: 886-7-822-5417 Email: sales@wontop.com Internet: http://www.wontop.com



Products listed in **bold** are WTE **Preferred** devices.

T3 suffix refers to a 13" reel. TB suffix refers to Ammo Pack.

Shipping quantity given is for minimum packing quantity only. For minimum order quantity, please consult the Sales Department.